

DPA3655QRT is a High End 3-IN/6-OUT digital speaker management system which maintains the same high quality hardware present in former QRT versions. Designed for maximum versatility, it provides all the processing and control necessary for both live and fixed installation use. Proving for any crossover configuration, it offers 3 analog inputs, 6 analog outputs, managed by a powerful MARANI® DSP Engine, for a full 96kHz processing. In addition to high performance 24 bit AD/DA Converters. Each input channel provides a choice of EQ with 18-band Parametric EQ, 3 ALL PASS Filter, Gain control, Noise Gate, RMS Compressor, Internal Generator, White/ Pink Noise

Generator, and configurable Delay. Each output offers up to 7-band of parametric equalization, in addition to the crossover filters which themselves provide slopes from 6dB/Octave up to 48dB/Octave. Each output path also features Peak Limiter and configurable Delay. The **DPA3655QRT** supports a full matrix mixing mode where inputs may be routed/mixed in any ratio to any output. For remote configuration and control the **DPA3655QRT** can be connected via USB or ETHERNET connections. The control remote PC software allows simultaneous control up to 32 units, setting all parameters and showing real time levels.



Features

Outstanding Performance

Excellent sonic performance with 24bit high end converters coupled with 96kHz sample rate
3 inputs, 6 outputs with full matrix mixing

Top-grade DSP Engine

18 band parametric equalization + 3 ALL PASS Filter per input channel
7 band parametric equalization per output channel
Each band can be switched to Bell, Shelving, HP/LP, Band Pass, Notch Filter
Crossover filters with slopes from 6dB/Octave up to 48dB/Octave including Butterworth, Bessel, Linkwitz-Riley
Process Overflow limiting
Each output features a precision dynamic range controller composed of a Limiter working on RMS value of the limiter's input

Adjustable Delay time up to 310 ms for every input channel and 270 ms for each output channel
Phase correction per input and output channel

Direct PC/Network Connection

Rear panel USB connector for direct PC communications
Ethernet Interface for system setup, monitoring and control via fully manageable remote PC software

Control

Front panel interactive LCD display for local access and configuration
Front panel 7-LED level meter indicators per channel
Simultaneous control up to 32 units via PC software
Up to 32 storable user presets
Security Lockout

Applications

- Auditoriums
- Houses of Worship
- Theaters
- Performing Art Centers
- Convention Centers
- Stadiums and Arenas
- Touring Musicians
- Stage Monitoring System digital



Audio

Analog Input	-----	3 x XLR electronically balanced
Analog Output	-----	6 x XLR electronically balanced
Minimum Load	-----	150 ohm
THD+N	-----	0.001% at 1kHz 0dBu
S/N	-----	>110dBA
Frequency Response	-----	20Hz - 20kHz; -0.5dBu at 20Hz and 20kHz
AD & DA Converters	-----	24bit - 96kHz

DSP & Processing

DSP Engine	-----	MARANI® DSP
DSP Resolution	-----	24bit (data) x 24 bit (coeff.), 54 bit accumulation registers, 96 bit precision on intrprocessing data
Parametric Equalization	-----	18 PEQ filters per input + 3 ALL PASS; 7 filters per output
Input/Output Gain	-----	From -18dB to +12dB by 0.1dBu resolution steps
Filter Type	-----	Bell, Shelving, HP/LP, Band Pass, Notch Filter
Filter Gain	-----	From -15dBu up to +15dBu by 0.5dBu resolution steps
Center Frequency	-----	from 20Hz up to 20kHz with 1Hz resolution steps
Filter Q/BW	-----	Bell Type: Q from 0.4 up to 128 in 100 steps Shelv/Hp/LP Type: Q from 0.1 up to 5.1 in 100 steps BandPass/Notch Type: Q from 4 up to 104 in 100 steps
Crossover Section HPF/LPF	----	Butterworth 6/12/18/24/36/48dB per octave Bessel 12/24dB per octave Linkwitz-Riley 12/24/36/48dB per octave
Internal Noise Generator	-----	White/Pink Noise; Level from -40dBu to 0dBu
Input All Pass	-----	Selectable as bypass, 1st and 2nd order
Input Noise Gate	-----	Threshold from -80dBu up to -50dBu, or not active
Input RMS Compressor	-----	Attack time from 1ms up to 1000ms; Release time from 10ms up to 1000ms
Output Peak Limiter	-----	Threshold from 20dBu up to -10dBu; Attack time from 5ms up to 200ms; Release time from 0.1sec up to 3sec
Headroom on Internal Overflow Processes	-----	12 dB
Routing	-----	Full matrix mixing mode
Delay	-----	310 ms 10.4us increment/decrement steps for each input, 270ms 10.4us increment/decrement steps for each output
Ground noise	-----	-90 dBu

General

Device Presets	-----	32 User Presets
Front Panel	-----	2x24 character LCD display with green LED backlight 7-LED meter per input channel -15dBu to +15dBu, clip and limiter mode 7-LED meter per output channel -15dBu to +15dBu, clip and limiter mode Blue LED (Edit) per channel Red LED (Mute) per channel NAV/PM1 Rotary encoder push button switch PM2, PM3, ENTER, ESC, UTILITY push button switches EDIT/MUTE push button per channel USB type B connector
Rear Panel	-----	3 x XLR female connector (Input) 6 x XLR male connector (Output) 1 x RJ45 for Ethernet connection (10/100 TCP-IP) 2 x Ground-lift toggle switch IEC C13 16A connector; Power on/off switch
Main AC	-----	90-240VAC (50/60Hz) - 40W
Dimensions	-----	19" x 1.75" x 9" (483x44x229mm) 1RU
Weight. Net/Shipping	-----	7.71 lbs (3.5 Kg) / 8.82 lb (4 Kg)